

1000W LED GROW LIGHT





Features:

- SIGNLITE PRIVATE MOULD
- Color: Samsung full spectrum white light
 +Osram 660nm Plant red light, mainly for hemp lighting.
- High quality Meanwell driver
- Wide input voltage AC100-277V or dimmable
- Best heat sink to get the best heat dissipation
- Easy to install and operate
- Energy saving, Instant start, NO flickering, NO humming, long service life, increase hemp output.
- 5years warranty



Applications:


• Mainly used for indoor hemp/Cannabis/Marijuana lightings.




Product Specifications:

Product Name	1000W LED Grow Light		
Model number	SL- G1000V1P02		
Power	1000W		
Input voltage	100-305VAC 50/60Hz		
LED Brand	Samsung and Osram (340pcs per bar)		
LED Driver	SS UL Driver		
Lumen	140,000LM		
Lumen efficiency	140LM/W		
ССТ	3500K		
CRI	>75		
PPF (380-780nm)	2800 μmol/S		
EFF	2.8 μmol/J		
Color	Full spectrum white light +660nm Plant red light		
Coverage	6ft×6ft		
Mounting height	≥ 6" (15.2cm) Above canopy		
Supplementation time	16-20H/day		
PF	>0.95		
Lamp size	1090*1070*143mm		
Angle	120°		
Housing color	White, with 2M plug		
Material	Aluminum + PC		
IP	IP54 (Indoor using)		
Lifespan	>50,000H		
N.W	18KG/PCS		
Working Temperature	-37°C~+55°C		
Operating Humidity	<95%		
Storage Temperature	-40°C~+80°C		

Dimension(mm)



Spectrum








Installation:

■ Installation Instruction

1.Lamp Fasten and Wire







1. Drill holes in the ceiling.


Place the expansion screw into the ceiling.

Install the lifting rope on the bracket first, then lock the lifting rope to the ceiling.



- 4. Connect the wires of the lamp to the bracket
- 5. Note: the connector male plug arrow is aligned with the female plug arrow
- Fit the screws to each bar, connect the plug to the socket connect the plug to the power source

Package:



Вох	QTY.	Size	N.W/CTN	G.W/CTN
Inner box	1PC	114.5*42*15.5 CM	18KG	18.5KG
Outer box	1PC	118*43.5*17.5 CM	18.5KG	21.5KG