

800W LED GROW LIGHT



Features:

- **SIGNLITE PRIVATE MOULD**
- Color: Samsung full spectrum white light + Osram 660nm Plant red light, mainly for hemp lighting.
- High quality driver
- Wide input voltage AC100-277V or dimmable
- Best heat sink to get the best heat dissipation
- Easy to install and operate
- Energy saving, Instant start, NO flickering, NO humming, long service life, increase hemp output.




Applications:

- Mainly used for indoor hemp/Cannabis/Marijuana lightings.


Product Specifications:

Product Name	800W LED Grow Light
Model number	SL-G800V1P02
Power	800W
Input voltage	100-277VAC 50/60Hz
LED Brand	Samsung 281b and Osram (340pcs per bar)
LED Driver	SS/JUSON UL Driver
Lumen	112,000LM
Lumen efficiency	140LM/W
CCT	3500K
CRI	>75
PPF (380-780nm)	2160 $\mu\text{mol}/\text{S}$
EFF	2.7 $\mu\text{mol}/\text{J}$
Color	Full spectrum white light +660nm Plant red light
Coverage	6ft×6ft
Mounting height	≥ 6" (15.2cm) Above canopy
Supplementation time	16-20H/day
PF	>0.95
Lamp size	1090*1070*143mm
Angle	120°
Housing color	White, with 2M plug
Material	Aluminum + PC
IP	IP54 (Indoor using)
Lifespan	>50,000H
N.W	15.1KG/PCS
Working Temperature	-37° C~+55° C
Operating Humidity	<95%
Storage Temperature	-40° C~+80° C






Dimension(mm)



Spectrum




PPFD Distribution:




Installation

■ Installation Instruction



1. Install the lifting rope on the bracket first, then hang the lifting rope to the ceiling.



2. As per above picture, insert each bar to each socket.



Please tear the film before lighting up.




AC 100-277V

3. Please tear the film before lighting up.

4. Connect the plug to the socket, connect the plug to the power source.

Package:



Box	QTY.	Size	N.W/CTN	G.W/CTN
box	1PC	117*42*15.5 CM	15.1KG	17.1KG